

Description

The obstacle avoidance robotic


Components and tools required

- Arduino UNO board
- Arduino sensor shield
- LN289 motor driver
- 2 geared motors
- Ultrasonic sensor with mount
- Chassy
- Wheels



Step 1:

Solder wires on the geared motors and the small switch like shown in the pictures below



You only need to solder one wire to the switch for now, The other will be soldered in the final steps, after it is mounted on the chassy.



Step 2:

Slide in 2 motor mounts in the designated slots on the chassy as shown in the picture.



Step 3:

- Put the 2 motors near the mounting supports.
- Add the second pair of mounting supports on the other side of the motors
- Fasten everything with 4 long screws that are provided in the kit




Step 4:

- Fasten the spacers for the caster wheel in the 4 holes at the back of the chassy.
- Mount the caster wheel on top of the spacers and secure it with screws.




Step 5:

Mount the wheels in the motor shafts, flip the chassy over and insert the rocker switch into the centre hole.




Step 6:

Mount the Arduino sensor shield on top of the Arduino



Step 7:

Mount the Arduino and sensor shield on the chassy, and connect the wire from the switch to VCC screw terminal on the sensor shield.



Step 8:

Mount the motor driver and battery holder using hot glue or double sided tape.




Step 9:

Mount the ultrasonic sensor in the holder and mount it with double sided tape on the servo, after that mount the servo - sensor assembly to the chasis.



Step 10:

Connect the electrical wires according to the schema below, and upload the provided code to the arduino.



Step 7: Programming the Robot

After you have finished connecting the motors to the motor shield you have now finished the assembly of robot. We now need to program it.

All you have to do is plug the UNO Board into your computer, load the Arduino software and write your code. Alternatively, you can use the sample code below:

Obstacle Avoiding Robot
www.phippselectronics.com

```
/*
 * Short code for the robot kit
 * When the ultrasonic sensor detects an obstacle the robot makes a left turn
 * and continues the forward movement
 *
 * It's possible that the motor speed may vary. in order to correct this you modify
the variables vitezaMotor1 or VitezaMotor2
 * with values between 0 and 255
 *
 *
 */

#include<Servo.h>

Servo SM;

// define the pins used by the ultrasonic sensor
#define echoPin2 2
#define trigPin2 13

//define motor speed
//modify the values if the motors are not spinning at the same speed
//motor 1
#define vitezaMotor1 140
//motor 2
#define vitezaMotor2 140

/*
define pins utilized for the motor control
pins enA and enB are used to control the motor speed using the PWM signal
//definiti pinii utilizaÈi pentru controlul motoarelor
//pinii enA si enB sunt folositi pentru a controla viteza motoarelor in functie
//de semnalul PWM

//pins in1, in2, in3 si in4 are used to control the dirrection of the motors
(forward or backward)
*/
```

Obstacle Avoiding Robot
www.phippselectronics.com

```
//pins used by the first motor
#define enA 11
#define in1 7 //LA
#define in2 6 //LB

//pins used by the second motor
#define enB 3
#define in3 5 //RA
#define in4 4 //RB

// forward = HIGH , backward = LOW
#define inainte HIGH
#define inapoi LOW

//declare the variables to determine the distance of the obstacles in front of the
robot
long duration1,duration2;
int distancel,distance2;

void directie (int dir1, int dir2)
{
    //if dir is HIGH, direction is forward
    //if dir is LOW, direction is backward

    //motor 1
    digitalWrite(in1, !dir1);
    digitalWrite(in2, dir1);

    //motor 2
    digitalWrite(in3, dir2);
    digitalWrite(in4, !dir2);

}

void viteza (int vit1, int vit2)
{
    analogWrite(enA,vit1);
    analogWrite(enB,vit2);
}
```

```
}

void forward() {
    digitalWrite(in1, HIGH);
    digitalWrite(in2, LOW);
    digitalWrite(in3, HIGH);
    digitalWrite(in4, LOW);
}

void backward() {
    digitalWrite(in1, LOW);
    digitalWrite(in2, HIGH);
    digitalWrite(in3, LOW);
    digitalWrite(in4, HIGH);
}

void leftward() {
    digitalWrite(in1, HIGH);
    digitalWrite(in2, LOW);
    digitalWrite(in3, LOW);
    digitalWrite(in4, HIGH);
}

void rightward() {
    digitalWrite(in1, LOW);
    digitalWrite(in2, HIGH);
    digitalWrite(in3, HIGH);
    digitalWrite(in4, LOW);
}

void Stop() {
    digitalWrite(in1, LOW);
    digitalWrite(in2, LOW);
    digitalWrite(in3, LOW);
    digitalWrite(in4, LOW);
}

void findDistance() {
    int duration;
    digitalWrite(trigPin2, HIGH);
    delayMicroseconds(10);
```

Obstacle Avoiding Robot
www.phippselectronics.com

```
digitalWrite(trigPin2, LOW);

duration = pulseIn(echoPin2, HIGH);
distance2 = (1 / 29.1) * (duration / 2);
delay(60);

}

void setup() {
    //the pins used by the ultrasonic sensor
    pinMode(trigPin2, OUTPUT);
    pinMode(echoPin2, INPUT);

    //every pins used by the L298N driver are set as OUTPUT
    //pinii utilizati de primul motor
    pinMode(enA,OUTPUT);
    pinMode(in1,OUTPUT);
    pinMode(in2,OUTPUT);

    //pinii utilizati de al doilea motor
    pinMode(enB,OUTPUT);
    pinMode(in3,OUTPUT);
    pinMode(in4,OUTPUT);

    analogWrite(enA, 220);
    analogWrite(enB, 240);

    SM.attach(10);
    SM.write(90);
    delay(3000);
}

void loop() {
    findDistance() ;

    if (distance2 > 35) {
        forward();
    } else {
```

```
    delay(60);  
    findDistance();  
    if (distance2 > 35) {  
        forward();  
    } else {  
        Stop();  
        SM.write(40);  
        delay(500);  
        findDistance();  
        if (distance2>35){  
            SM.write(90);  
            delay(1000);  
            rightward();  
            delay(500);  
            Stop();  
        }else{  
            SM.write(130);  
            delay(1000);  
            findDistance();  
            if (distance2>35){  
                SM.write(90);  
                delay(1000);  
                leftward();  
                delay(500);  
                Stop();  
            }else{  
                SM.write(90);  
                delay(1000);  
                rightward();  
                delay(1500);  
                Stop();  
            }  
        }  
    }  
}
```

Disclaimer: Libraries, example code, diagrams and resources are provided as an additional free service and are not sold as part of this product. Phipps Electronics Pty Ltd does not provide any guarantees or warranties as to their accuracy or fitness for purpose.